

HEIDENHAIN



Preliminary
Product Information


ERP 1080 D*plus*


High-Accuracy Angle Encoder without Integral Bearing

ERP 1080 Dplus

- Very high system accuracy
- Resilient angle measurement
- · Low mass and low mass moment of inertia
- Consisting of a scanning ring and a circular scale







- ☐ = Bearing of mating shaft
- ® = Reference mark
- K1 = Required mating dimensions
- K2 = Required mating dimensions with centering collars
- 1 = Direction of shaft rotation for ascending position values
- 2 = Marks for circular scale centering (3 x 120°)
- 3 = Mark for 0° position
- 4 = Centering collar for scale hub
- 5 = Centering collar for scanning unit
- 6 = Screw: ISO 4762 M5x16 8.8 tightening torque: 550 Ncm ±33 Ncm; material bonding threadlocker required

- 7 = Screw: ISO 4762 M4x12 8.8 tightening torque: 220 Ncm ±13 Ncm; material bonding threadlocker required
- 8 = Customer's mounted parts

Material: Stee


Tensile strength: $Rm > 600 \text{ N/mm}^2$ Yield point: $Re > 400 \text{ N/mm}^2$ Shear strength: $Tau > 390 \text{ N/mm}^2$


Elasticity module: 20 °C: E >200000 N/mm 2 ... 215000 N/mm 2 Coefficient of thermal expansion: 20 °C: (10<alpha<13) x 10 $^{-6}$ 1/K

9 = Mounting surface must be clean and free of grease

10 = Hub shown rotated by 45°

11 = Depth of thread





Specifications

Encoder	ERP 1080 Dplus			
Interface ¹⁾	4 x ~ 1 V _{PP}			
Reference mark signal	Square-wave pulse			
Cutoff frequency -3 dB	≥ 500 kHz			
Electrical connection Four 1.5 m cables with 15-pin D-sub connector (male)				
Cable length ¹⁾	with HEIDENHAIN cable: ≤ 20 m; during signal adjustment with the PWM 21: ≤ 3 m			
Voltage supply ¹⁾	DC 5V ±0.5V			
Current consumption ¹⁾	≤ 150 mA (without load)			
Vibration 55 Hz to 2000 Hz	\leq 200 m/s ² (EN 60068-2-6)			
Shock: 6 ms	\leq 1000 m/s ² (EN 60068-2-27)			
Operating temperature	0 °C to 40 °C			
Storage temperature	−20 °C to 60 °C			
Mass Scanning ring Connector Cable Scale hub	≈ 1.1 kg (without cable) ≈ 75 g ≈ 22 g/m ≈ 289 g			

¹⁾ Separate electrical connection for each scanning head

	ERP 1080 Dplus
Measuring standard	OPTODUR circular scale on glass
Signal periods*	63000
System accuracy	±0.4"
Position error per signal period ¹⁾	±0.02"
RMS position noise (500 kHz)	0.001"
Reference marks	One
Outside diameter of scanning ring	194 mm
Inside diameter of hub	104 mm
Outside diameter of circular scale	151 mm
Mech. permissible speed	≤ 950 rpm
Elec. permissible speed	≤ 475 rpm
Moment of inertia of the scale hub	$1.1 \cdot 10^{-3} \text{ kgm}^2$
Protection EN 60529	Complete, mounted encoder: IP00

The position error within one signal period and the accuracy of the graduation together yield the encoder-specific error; for additional mounting and bearing errors of the measured shaft, see *Measuring accuracy* in the *Modular Angle Encoders with Circular Scale* brochure.

5

Transferable accuracy

In order to achieve accuracies in the high-end range, customers must often perform a very complex and time-consuming calibration of the entire machine. Under the motto "transferable accuracy," HEIDENHAIN contributes to facilitating the mounting process for the customer and to transferring the high accuracy of our encoders to the customer's application without any losses. For the ERP 1080 D*plus* encoders, this is achieved based on the following features:

- Sturdy, mechanical interface for mounting on the customer side
- Four scanning heads for position calculation for resilient angle measurement

Electrical connection

The ERP 1080 D*plus* angle encoder provides four separate connections (D-sub, 15-pin) with 1 V_{PP} interface. The EIB 74x signal converters that are available from HEIDENHAIN can be used to operate the product. The product can also be connected to downstream electronics from third-party suppliers if they provide four 1 V_{PP} inputs.

Position calculation with an EIB 74x or downstream electronics from third-party suppliers

For the system to be able to reach the specified accuracy, the positions of all scanning heads need to be averaged.

$$X_{avg} = \frac{(X1_{abs} + X2_{abs} + X3_{abs} + X4_{abs})}{4}$$

X1_{abs} ... X4_{abs}: Positions of the scanning


X_{avq}: Arit

Arithmetic mean value of inputs X1_{abs} to X4_{abs}

Electrical connection

Pin layout

Pin layout



Shield lies on housing; U_P = Power supply voltage

Sensor: The sense line is connected in the connector with the corresponding power line.

Vacant wires and pins must not be used.

7

¹⁾ Required for signal adjustment with the PWM 21

Cables

Adapter cables and connecting cables for 1 VPP

PUR $6 \times (2 \times 0.19 \text{ mm}^2)$; $A_P = 2 \times 0.19 \text{ mm}^2$			
PUR $4 \times (2 \times 0.14 \text{ mm}^2) + (4 \times 0.5 \text{ mm}^2); A_P = 2 \times 0.5 \text{ mm}^2$			Ø 6 mm ¹⁾
Adapter cable with 15-pin D-sub connector (female) and 12-pin M23 connector (male)		331693-xx	355215-xx
Adapter cable with 15-pin D-sub connector (female) and 15-pin D-sub connector (male)		335074-xx	355186-xx
Connecting cable with 15-pin D-sub connector (female) and stripped cable end	├	332433-xx	355209-xx
Connecting cable with 15-pin D-sub connector (female) and 15-pin D-sub connector (female) with pin layout for the IK 220		335077-xx	349687-xx
Signal cablewith stripped cable ends (for 15 pins)	*	816317-xx	816323-xx

¹⁾ Cable length for Ø 6 mm: max. 9 m A_P: Cross section of power supply lines

HEIDENHAIN

DR. JOHANNES HEIDENHAIN GmbH Dr.-Johannes-Heidenhain-Straße 5 83301 Traunreut, Germany **2** +49 8669 31-0 FAX +49 8669 32-5061 info@heidenhain.de

www.heidenhain.com

This Product Information document supersedes all previous editions, which thereby become invalid. The basis for ordering from HEIDENHAIN is always the Product Information document edition valid when the order is placed.



(Further information:

Comply with the requirements described in the following documents to ensure correct and intended operation.

- Brochure: Modular Angle Encoders with Circular Scale
- Brochure: Interfaces of HEIDENHAIN Encoders

1401414-xx 1078628-xx